

POWERI – generating sets powered by HATZ – diesel

TYPE NO	POWERI 2801 DHZ	POWERI 5001 DHZ	POWERI 6501 DHZ	POWERI 7503 DHZ	POWERI 7/10 DHZ
Rating VA	2 800	5 000	6 500	7 500	10 000
Contin. Rating W	1 900	3 300	5 000	5 200	6 000
Protection frame	yes	yes	yes	yes	yes
ENGINE	1B20	1B30	1B40	1B40	1B40
Nominal hp	4,2	6,3	9,3	9,3	9,3
Rating hp/3000 rpm	3,8/2,8	5,6/4,1	8,4/6,2	8,4/6,2	8,4/6,2
Displacement cc	232	347	462	462	462
Oil guard	yes	yes	yes	yes	yes
Fuel tank litres	3	5	5	5	5
Consumt. max l/h	0,4-0,6	0,5-1,4	0,5-2,3	0,5-2,3	0,5-2,3
Noise dB	77	78	82	82	82
Cooling	air	air	air	air	air
GENERATOR	S15W	S16W	S16F	T16F	T20FS
Rating VA	2 800	5 000	6 500	7 500	10 000
Voltage V	230	230	230	230/400	230/400
Circuit breaker A	10	15	20	4 x 10	4 x 16
Resid.cur.device	-	-	-	yes	yes
Socket 230 V	2 pcs	2 pcs	2 pcs	2 pcs	2 pcs
Socket 400 V	-	-	-	1 pc	1 pc
Warranty years	1	1	1	1	1
Dimens. l-w-h cm	70-50-50	80-50-59	80-50-59	80-50-59	80-50-59
Weight kg	50	68	93	99	124



POWERI 5001 DHZ-S (with electric start)



POWERI 7503 DHZ-S (with electric start)



POWERI 7503 DHZ

Optionals:

- Electric start
- Wheelsets
- Extra fuel tanks
- V-, A-, Hz- ja H-meters
- Remote control
- Loadstarting
- Automatic mains failure control system
- Weather / noise protection